

## *LTT24 – fast, flexible and precise*



## LTT24 – High Speed measurement technology


**Winner**  
of the  
**MESSTEC & SENSOR**  
Masters 2013  
**AWARD**



The multifunctional, patented real-time data acquisition device LTT24 with 24 Bit ADC and 4 MSample/s per channel, including the functionality of a measuring amplifier for volts, current, ICP®, strain gage, charge, resistance, pulse, temperature etc.



*Liquid metal flows*



*Electric motors*



*Tape drive  
replacement*



*Automotive industry*



*Power quality*

## LTT24 – up to 4 MHz at 24 Bit

### AT FULL SPEED WITH HIGHEST PRECISION

- 24 Bit AD-conversion at up to 4 MHz sampling rate
- Digital measurements accurate to nanoseconds
- Pulse/counter inputs: 832 MHz  $\Delta$  1.20 ns resolution
- 20 Bit analog outputs up to 2 MHz

### INCREDIBLY FLEXIBLE

- Recording with a PC or an internal SSD (500 GB)
- Modular housing concept 4, 8, 12, 16 channel inserts
- USB 3.0 | USB 2.0 and Gigabit Ethernet interface to PC
- Synchronization interface for device cascading of multiple LTT24 devices
- Digital I/O and synchronization interface
- Extendable at any time

### INCREDIBLY PRECISE

- Best signal quality (16 ENOB – Effective Number of Bits)
- Best CMRR – Common Mode Rejection Ratio
- Best galvanic isolation
- Flat bandwidth: DC - 1 MHz or 1.7 MHz

### HIGH PRECISION INPUTS AND OUTPUTS

- For volts, current, charge, ICP®, strain gage, LVDT, resistance, also All-in-one
- Sensor supply output: constant voltage, constant current, carrier frequency
- Single-ended and differential-ended: AC or DC
- Status LEDs for all channels

### SOFTWARE

- LTTpro: Control and visualization software
- LTT2API: Library for integration into customer applications
- Compatible with DASyLab, LabVIEW, Matlab, FlexPro, Famos etc.



LTT24 front



LTT24 back

# LTT24 – Fields of application

## HIGH SPEED MEASUREMENT TECHNOLOGY IN USE

The LTT24 is used for a wide variety of applications in almost all industries. We will give you concrete examples of how you can benefit from our fast, flexible and precise measurement technology.



*Military*



*Offshore  
wind farms*



*Universities*



*EMC measurements  
in rail traffic*



*OEM test bench  
construction*



*Ultrasonic /  
Underwater acoustics*

[www.tasler.de](http://www.tasler.de)

### FATIGUE AND CRACK DETECTION

Material tests with structure-borne sound, DMS, ICP® and charge



### PRODUCTION MONITORING

Development of turbochargers



**POWER  
MEASUREMENT**  
on battery-powered  
electric motors



### TRANSIENT RECORDERS

with extensive  
sensor support



### AEROSPACE

Qualification test  
of satellite systems



## Labortechnik Tasler GmbH

Friedrich-Bergius-Ring 15  
97076 Würzburg, Germany  
Fon +49 931 359 610  
Fax +49 931 359 6150

[kontakt@tasler.de](mailto:kontakt@tasler.de)  
[www.tasler.de](http://www.tasler.de)

# LTT24 – Technical Data

## Transient recorder including Sensor-Preamplifiers

Technical Specifications – Optional Specifications marked with \*

### Available Housings

LTT24-4	4 channel housing: 142 x 400 x 75 mm <sup>3</sup> / 3,7 kg
LTT24-8	8 channel housing: 244 x 400 x 75 mm <sup>3</sup> / 5,9 kg
LTT24-16	16 channel housing: 447 x 400 x 75 mm <sup>3</sup> / 10,4 kg

### Data Transfer Rates

Internal SSD	256 MByte/s*
PC with USB	170 MByte/s (USB 3.0) 35 MByte/s (USB 2.0)
PC with Gigabit LAN	27 Mbyte/s*

### Input Characteristics

Quantization	24 Bits
max. Sampling Rate	4 MSample/s per channel
max. Bandwidth	DC – 1.7 MHz
Filter	analog: 1.7 MHz low pass filter digital: a variety of selectable filters
Inter-Channel Phase Difference	< 1 ns
Input Connectors	BNC and DIN
Galvanic Isolation	±200 V
Volt Input Ranges	±250 mV, ±5 V, ±50 V, ±200 V*
Volt Input Impedance	1MΩ_50pF, [10MΩ_5pF at ±200 V]*
Volt Input Couplings	single-ended (AC/DC), differential (AC/DC)
Current Input	±50 mA range with internal 5 Ω shunt resistor

### Number of Channels

max. No. of Channels per Device	4, 8 or 16 (dependent on housing)
max. No. of Devices	1024
Synchronization*	yes (max. delay between devices: ±1 ns)
External Clock*	1 input and 1 output with 3.3 V LVPECL
External Trigger*	1 input and 1 output with 5 V TTL
Digital Inputs*	16 inputs and 16 outputs with 5 V TTL

Dynamic Range	Range	Bandwith		
		5 kHz	50 kHz	1 MHz
	±50 V	116 dB	110 dB	100 dB
	±5 V	118 dB	112 dB	101 dB
	±250 mV	105 dB	97 dB	85 dB
ENOB (THD + noise) effective number of bits	Range	effective bits	dB @ 125 kHz sampling rate	
	±50 V	typ 15.6 Bit	-96 dB	
	±5 V	typ 15.9 Bit	-98 dB	
	±250 mV	typ 14.6 Bit	-90 dB	
Crosstalk	< -120 dB (DC – 200 kHz)			
CMRR without Trimming common mode rejection ration	Range	0-20 kHz	0-100 kHz	0-1 MHz
	±250 mV	typ 95 dB	87 dB	70 dB
	±5 V	typ 88 dB	74 dB	55 dB
	±50 V	typ 78 dB	73 dB	53 dB
CMRR with Trimming* common mode rejection ration	Range	0-20 kHz	0-100 kHz	0-1 MHz
	±250 mV	> 100 dB	88 dB	70 dB
	±5 V	> 100 dB	75 dB	55 dB
	±50 V	> 100 dB	74 dB	53 dB
Input Protection	±17.5 V @ range ±250 mV, ±5 V; ±175 V @ range ±50 V; ±220 V @ range ±200 V			

## Operating Conditions

Power Supply	12-16 VDC (absolute max. rating 10-35 VDC)
	11 W typical per channel without sensor supply
	external power supply: 100-240 VAC
Environmental Temperature	+10 °C to +40 °C
Extended Temperature Range	0 °C to + 50 °C on request
Operating System	Windows 7 / 8 / 10, Linux and others

## Data Recording

RAM	32 MByte per channel 512 MByte RAM with 16 channels
Interface to PC	USB 3.0, USB 2.0, Gigabit Ethernet*
Recording Media	internal RAM, internal SSD*, PC's hard disk
Size of internal SSD	500 GB*

## Signal Conditioning

Strain Gage*	full-, half-, quarter-bridge, sense, no sense constant voltage supply: 0 ... 10 V, 0 ... 20 V* input coupling: AC and DC
IEPE (ICP®)*	constant current supply: 0 ... 10 mA; input coupling: AC and DC
Resistance*	input coupling: AC and DC; 2-wire, 3-wire and 4-wire
Charge*	1 mV/pC, range: $\pm 5$ nC (optional up to $\pm 500$ nC) high-pass: 0.15 Hz; 1.5 Hz; 15 Hz auto charge clear; manual clear
LVDT*	carrier frequency with up to 100 kHz and 0 ... 5 V Amplitude synchronous demodulation; unipolar and bipolar output
Pulse/Counter Input*	signal input: $\pm 30$ V input coupling: AC and DC time resolution 1.20 ns (832 MHz) direction detection; zero marker

## Analog Output Characteristics

No. of Channels per Device	one analog output channel for each analog input channel
Synchronization of several Devices	yes (max. delay between devices: 2 ns)
Sampling Rate	max. DAC rate 2 MSample/s per channel
max. Bandwidth	DC – 500 kHz
Quantization	18 Bit, 20 Bit*
Output Impedance	100 $\Omega$
Connector	BNC
Galvanic Isolation	input to output of same channel: yes ( $\pm 200$ V) output to LTT24 housing: no
Output Ranges	$\pm 10$ V, $\pm 5$ V; $\pm 500$ mV, $\pm 250$ mV
Coupling	DC
DC Offset	digital
Dynamic Range	100 dB with 20 Bit DAC*
Inter-Channel Phase Difference	< 2 ns
Output Signal Sources	monitoring: online ADC data from analog input replay: recorded ADC data from internal SSD arbitrary function generator: PC data from internal SSD

Specifications are subject to change without notice.